

Document title	CdC_DCOS_V2.35_JPA_50_Automated_RF_Part_3_SemicParamAnalyzer.docx
-----------------------	---

Réf. Chrono	DRT-LETI-DCOS-S3C-LTA-25-01-000203
--------------------	------------------------------------

DEFI	FONCTION	NOM
Rédacteur	Auteur – Responsable Equipment	L. LUCCI
Vérification	Chef de Laboratoire	B. DURIEZ
Vérification	Chef de Service	F. GAILLARD
Approbation	Adjointe Opération CdD	C. ARNAUD
Diffusion	Ingénieur Sécurité	S. REYNAUD
Diffusion	Travaux Neufs	V. AMPHOUX
Diffusion	Informatique	A. GROSSE
Diffusion	CdD DCOS	O. FAYNOT

SUMMARY

1	PURPOSE	5
2	PROCESS OR MEASUREMENT SPECIFICATIONS	6
3	EQUIPMENT TECHNICAL SPECIFICATIONS	9
3.1	EQUIPMENT DESCRIPTION	9
3.2	HARDWARE	9
3.2.1	Pumping system	9
3.2.2	Gas/chemical lines	9
3.2.3	Equipment consumption monitoring	9
3.2.4	Idle mode management and interface with peripheral sub-equipments	9
3.2.5	Flammable gas management	9
3.2.6	Temperature control	9
3.2.7	Vibrations	10
3.2.8	Other	10
3.3	SOFTWARE	10
3.3.1	IT configuration	10
3.3.2	Antivirus and data back-up	10
3.4	TRANSFER AND HANDLING OF WAFERS	11
3.4.1	Wafers specifications	11
3.4.2	Load ports	11
3.4.3	Handling and contact surfaces	11
3.4.4	References of wafer carriers used on equipment	11
3.4.5	Handling system reliability	11
3.5	MINI ENVIRONMENT	11
3.5.1	Check of the physical characteristic of the air	11
3.5.2	ESD (Electrostatic Discharge)	11
3.5.3	Particle checks	12
3.6	INTERFACE WITH THE REST OF THE CLEAN ROOM AND ITS ORGANISATION.	12
3.7	CONTAMINATION	12
3.7.1	Particle contamination	12
3.7.2	Metallic contamination	12
3.8	SPECIFIC INTERFACE WITH FACILITIES	12
3.8.1.1	If CMP type equipment (Chemical Mechanical Polishing)	12
3.8.1.2	If WET BENCH type equipment	12
4	GENERAL BUILDING, FLUIDS, ELECTRICITY, ENVIRONMENT SPECIFICATIONS	12
4.1	ENVIRONMENT OF THE EQUIPMENT	12
4.1.1	Building specifications	12
4.1.2	Building fluids	12
4.1.3	Building power network specifications	12
4.1.4	Adaptation of the machine to the power network	13
4.1.5	Uninterruptible power supply (UPS)	13
4.2	MANAGEMENT OF THE ENVIRONMENT	14
4.2.1	Process Cooling Water	14
4.2.2	Exhaust and other internal equipment air systems	14
4.2.3	Segregation of liquid effluents	14
4.2.4	Case of DI return or recycling of ultrapure water	14
4.2.5	Gaseous effluents	14
4.2.6	Odours	14
5	SAFETY	14
5.1	EC CONFORMITY	15
5.2	RISKS CONNECTED WITH FACILITIES	16

5.3 RISKS CONNECTED WITH FIRE	17
5.4 RISKS CONNECTED WITH CHEMICAL PRODUCTS	17
5.5 RISKS CONNECTED WITH HANDLING	19
5.6 RISKS CONNECTED WITH PRESSURISED EQUIPMENT	19
5.7 RISKS CONNECTED WITH WORK AT HEIGHT	19
5.8 RISKS CONNECTED WITH LASER RADIATION	19
5.9 RISKS RELATED TO SOURCES OF IONIZING RADIATION (RADIOACTIVE SOURCES / ELECTRIC GENERATORS OF IONIZING RADIATION, ETC.)	20
5.10 RISKS CONNECTED WITH NOISE	21
5.11 RISKS CONNECTED WITH TEMPERATURE	21
5.12 SIGNALING	21
5.13 INTERVENTION CONDITIONS ON THE CEA-LETI SITE	21
6 SUSTAINABLE DEVELOPMENT	22
6.1 CORPORATE SOCIAL RESPONSIBILITY (CSR)	22
6.2 SUSTAINABLE DEVELOPMENT AND DEVELOPMENT OF THE LOCAL ECONOMIC FABRIC	22
6.3 ENERGY PERFORMANCE	22
7 EQUIPMENT DELIVERY CONDITIONS	23
8 CONDITIONS FOR INSTALLING EQUIPMENT	23
9 TRAINING & LEARNING	23
10 DOCUMENTATION	23
11 WARRANTY	24
11.1 WARRANTY CONDITIONS	24
11.2 SUPPORT DURING WARRANTY	24
11.3 EQUIPMENT PERFORMANCE INDICATORS	24
12 MAINTENANCE	24
12.1 SPARE PARTS	24
12.1.1 List of spare parts:	24
12.1.2 Process-kit :	24
12.1.3 Storage area	25
12.2 MAINTENANCE CONTRACT	25
12.3 COST OF OWNERSHIP (COO)	25
13 CHECKS & TESTS	25
13.1 CHECKS AND TESTS AT THE FACTORY (FACTORY ACCEPTANCE TESTS)	25
13.2 CHECK UPON DELIVERY & AT UNPACKING	25
13.3 INSTALLATION & COMMISSIONING	26
13.4 QUALIFICATION	26
13.5 ACCEPTANCE	27
13.6 END OF WARRANTY	27
14 INSTALLATION PREPARATION SCHEDULE	27
15 APPENDICES	29
APPENDIX A: Summary of Contractor's comments	29
APPENDIX B: or general fluids to building 41-01&02 or 41-03 or 4007 or 52B or 52C	30
APPENDIX C: Definition of Availability	33
APPENDIX D: Specification for delivery of equipment subject to the European "machinery" Directive 2006/42/CE	35

APPENDIX E: Specification relating to documents and manuals to be provided with the equipment	37
APPENDIX F: Selection of protection against risks connected with moving parts Characteristics required for guards and protective devices	42
APPENDIX G: Transfer and handling of wafers	44
APPENDIX H: Datasheet for tool installation	46
APPENDIX I: Risk Identification Sheet	47
APPENDIX J: SECS/GEM Compliance	48

1 PURPOSE

For its research activities targeted at developing 10 nm and beyond fully-depleted SOI technologies, CEA-LETI is willing to purchase a semiconductor parameter analyzer. This equipment and is intended for precise device electrical characterization and shall supports all aspects of device measurement, in the version described in this specifications form or in the version including optional upgrades.

Typical device measurements performed on a semiconductor parameter analyzer are, as examples: quasi-static current-voltage characteristics (IV), low frequency capacitance-voltage characteristics (CV) and fast pulsed IV tests. Measurements are made on two, three, four or more terminal semiconductor devices. The equipment is ideally in the form of a rack holding a series of modules each enabling a specific measurement on a specific device terminal.

The instrument shall be completely controllable both in stand-alone configuration (with screen and keyboard, internal or external) or via SCPI/GPIB commands send by external control unit on LAN/ethernet and/or GPIB bus and/or USB bus.

Documents to be provided by the Contractor during the tender process

- ✓ The Contractor must complete and deliver to CEA-LETI **Appendix A: Summary of Contractor's comments** and put any comments in this section (the Contractor must not add any comments in the main text).
- ✓ The Contractor must complete and deliver to CEA-LETI **Appendix H: Datasheet for Tool Installation**.
NB: The datasheet information allows CEA-LETI to design the fluid PID* and the electrical PID*. These PIDs are then sent for verification and approval to the equipment Contractor. Hook Up and Fit Up will start after the official validation of PIDs by the equipment Contractor. (* Piping and Instrumentation Diagram)
- ✓ The Contractor must complete and deliver to CEA-LETI **Appendix I: Risk Identification Sheet**
- ✓ The Contractor must complete and deliver to CEA-LETI **Appendix J: SECS/GEM Compliance**
- ✓ A forecast packing list

2 PROCESS OR MEASUREMENT SPECIFICATIONS

As summarized in chapter 1 the system will consist of a rack or mainframe holding one or more measurement units (SMU) and control electronics. The Contractor will have to demonstrate its capacity to reach the specifications to which he complies, by presenting results obtained on the proposed tool.

Process 1 Mainframe functions and software ergonomics - IV measurements

N° du test	Description du test	Specification
Test 1	<p>Creation of typical trans-conductance measurement setup directly on the GUI of the instrument:</p> <ul style="list-style-type: none"> - specify a gate voltage sweep between 0V and 5V, in 10mV steps on a definite drain voltage list (e.g 50mV, 0.5V, 1V, 10V, 200V) - specification of current and power compliance limits (10mA or 10mW) - specification of different quasi-static sweep parameters such as hold and delay times. 	<p>1. Main device terminal (e.g. drain ou collector)</p> <p><i>I/V ranges:</i></p> <ol style="list-style-type: none"> 1.1 $V \geq 200$ V for imposed voltage 1.2 $I \geq 1$ A for currents 1.3 full four-quadrant operation: any combinations of positive and negative values allowed <p><i>I/V measurement resolution:</i></p> <ol style="list-style-type: none"> 1.4 10 fA or less for measured currents 1.5 2 μV or less for measured voltages. <p>2. Biasing terminals (e.g. gate, base, substrate, wells, etc.):</p> <p>2.1 at least four biasing terminals in use in addition to the Main terminal</p> <p><i>I/V ranges:</i></p> <ol style="list-style-type: none"> 2.1 $V \geq 100$ V for imposed voltage 2.2 $I \geq 100$ mA for currents 2.3 full four-quadrant operation: any combinations of positive and negative values allowed <p><i>I/V measurement resolution:</i></p> <ol style="list-style-type: none"> 2.4 1 fA or less for measured currents 2.5 1 μV or less for measured voltages. <p>3. Embedded software ergonomics</p> <ol style="list-style-type: none"> 3.1 Real time plotting of measured quantities during measurement 3.2 Real time plotting of derived quantities or extractions (e.g. $gm=dI/dV$) during the measurement 3.3 Export of graph on .png or .jpg format
Test 2	<p>Identification of a series of SCPI/GPIB commands so that the same measurement procedure as in test 1 can be automatically set up from an external PC connected on a GPIB bus using MATLAB and/or python and/or labview</p>	<p>1. Main device terminal (e.g. drain ou collector)</p> <p><i>I/V ranges:</i></p> <ol style="list-style-type: none"> 1.1 $V \geq 200$ V for imposed voltage 1.2 $I \geq 1$ A for currents 1.3 full four-quadrant operation: any combinations of positive and negative values allowed <p><i>I/V measurement resolution:</i></p> <ol style="list-style-type: none"> 1.4 10 fA or less for measured currents

		<p>1.5 2 μV or less for measured voltages.</p> <p>2. Biasing terminals (e.g. gate, base, substrate, wells, etc.):</p> <p>2.1 at least four biasing terminals in use in addition to the Main terminal</p> <p><i>I/V ranges:</i></p> <p>2.1 $V \geq 100$ V for imposed voltage</p> <p>2.2 $I \geq 100$ mA for currents</p> <p>2.3 full four-quadrant operation: any combinations of positive and negative values allowed</p> <p><i>I/V measurement resolution:</i></p> <p>2.4 1 fA or less for measured currents</p> <p>2.5 1 μV or less for measured voltages.</p>
Test 3	Export of the measurement data	<p>1. export of the measured data in plain txt/ASCII format</p> <p>2. export of the measured data in Microsoft Excel compatible format (e.g. csv)</p>

During the test a PC equipped with a GPIB interface and a python or MATLAB or labview interpreter will be provided by the CEA-LETI. During the test a typical 4 terminal MOSFET will be provided by the CEA.

Process 2 Mainframe functions and software ergonomics - CV measurements (optional)

N° du test	Description du test	Specification
Test 1	<p>Creation of a capacitance measurement setup directly on the GUI of the instrument for a two terminal device (Hi and Low terminals):</p> <ul style="list-style-type: none"> - specify a capacitance vs. Voltage sweep - specify a capacitance vs. frequency sweep - specify a capacitance vs. time sweep - specification of any of the above three test while other units are providing any combination of DC power to three device terminals. 	<ol style="list-style-type: none"> 1. Possible bias range for the Hi terminal up to 25V or above 2. Minimal frequency range 1kHz to 5 MHz 3. Minimal frequency resolution of 1mHz 4. Real time plotting of measured quantities (Capacitance vs Voltage/Frequency/time) during measurement
Test 2	<p>Identification of a series of SCPI/GPIB commands so that the same measurement procedure as in test 1 can be automatically set up from an external PC connected on a GPIB bus using MATLAB and/or python and/or labview</p>	<ol style="list-style-type: none"> 1. Possible bias range for the Hi terminal up to 25V or above 2. Minimal frequency range 1kHz to 5 MHz 3. Minimal frequency resolution of 1mHz
Test 3	<p>Export of the measurement data</p>	<ol style="list-style-type: none"> 1. export of the measured data in plain txt/ASCII format 2. export of the measured data in Microsoft Excel compatible format (e.g. csv)

*During the test a PC equipped with a GPIB interface and a python interpreter will be provided by the CEA-LETI.
During the test a typical 2 terminal device will be provided by the CEA.*

3 EQUIPMENT TECHNICAL SPECIFICATIONS

3.1 Equipment description

As mentioned in the general description in chapter 1, the semiconductor parameter analyzer (the instrument in the rest of the document) shall be in the form of a mainframe housing with optional modules.

The instrument must be compatible with standard 19-inches instrument racks. The instrument shall have an embedded screen and provide jack for connecting an optional external monitor. An optional keyboard and mouse connector must also be present.

The instrument shall include an 'interlock' mechanisms to prevent the application of dangerous voltages or currents. The Instrument shall connect to the ground of a 300 mm wafer handling probe station via a triaxial connector.

The instrument shall be fully controllable via SCPI commands on a GPIB/IEEE 488 network.

The instrument will come equipped with a number of modules or slots. Some of this slots will be quoted as optional and will be included or not depending on budget considerations.

In a **mandatory configuration** the instrument will be equipped with:

- one high power module capable of delivering up to 200 Volts (if in voltage source mode) or up to 1 Ampere (if in current source mode), and provide force and sense kelvin connection to the probe tips of the on-wafer probe station with two triaxial cables.
-
- Four standard modules able to deliver at least 42 Volts or 100 mA. The four modules also shall be provide a kelvin connection by means of two triaxial cables each.
-

The high-power module and the four standard power modules shall comply to the minimal requirements detailed in Chapter 2.

In an **optional configuration, quoted specifically apart from the first mandatory configuration**, in addition to the above-mentioned specifications (mandatory configuration) the instrument will be equipped with:

- a high frequency capacitance module capable of measuring frequency dependent capacitance between two electrical terminals (Hi Low).

3.2 Hardware

3.2.1 Pumping system

Not applicable.

3.2.2 Gas/chemical lines

Not applicable.

3.2.3 Equipment consumption monitoring

Not applicable.

3.2.4 Idle mode management and interface with peripheral sub-equipments

Not applicable.

3.2.5 Flammable gas management

Not applicable.

3.2.6 Temperature control

Not applicable.

3.2.7 Vibrations

Not applicable.

3.2.8 Other

Not applicable.

3.3 Software

3.3.1 IT configuration

Connection to the external network

Not applicable.

Connection to the internal network (intranet)

Not applicable.

Restoration of the system:

Contractor agrees to provide CEA-LETI with:

- the procedure enabling complete backup of the embedded hard drives
- the hardware required for correct application thereof

It will train the CEA-LETI maintenance staff in proper application of this procedure

A backup will be performed for tool acceptance.

Licenses

Contractor agrees to deliver the equipment with all the operating licenses enabling it to be used by CEA-LETI.

Software update and upgrade

Contractor shall systematically provide the CEA-LETI with update (bug correction, etc.), upgrade and the latest version of the software as soon as it becomes available and shall install them free of charge during the warranty period. After the warranty has expired, the Contractor will keep CEA-LETI informed of any upgrade or new version that improves the functionality and provide the price conditions if the CEA-LETI request them.

Notwithstanding the warranty expiration, the Contractor will perform the software modifications needed to fix any bugs and therefore maintain the original functionality of the software at no cost to the CEA-LETI. The modifications connected with a correction (bugs, etc.) shall be supplied and installed free of charge.

Through-the-wall installation

If the equipment is installed in through-the-wall mode, user interface stations shall be available in both white and grey areas. The two control stations shall not be active at the same time.

3.3.2 Antivirus and data back-up

Antivirus :

- **Only required for computers running with Windows type of Operating System, and directly connected to CEA-LETI network.**

There are 3 Antivirus solutions provided by CEA-LETI:

- Symantec EndPoint Protection, version 14 or above
- McAfee OfficeScan v8.8 or above
- TrendMicro Apex One

If none of those antiviruses are compatible with the equipment, Contractor must provide a qualified antivirus.

In all cases, Contractor must specify a qualified configuration of antivirus, including:

- List of exclusions required for real time control (Symantec EndPoint Protection)
- List of executables usually used during equipment operation (McAfee Application Control)

- **Required for all computers connected to CEA-LETI network, whatever the Operating System is**

Provider must specify in his technical proposal if a qualified local firewall is available on the computer connected to CEA-LETI network.

Data back-up:

CEA-LETI performs back-up copy of all data stored on all computers and associated peripheral devices of the equipment.

This is achieved doing both:

- a snapshot of all storage disks, with a tool like "Symantec Ghost"
- an automatic data copy, capturing (on a periodic basis) data updates during equipment operation

In case the equipment complies with such methodology, the Contractor must specify in his technical proposal the process to generate files dedicated to the periodic back-up.

If the equipment is not compatible with this methodology, the Contractor must specify in his technical proposal the way to create back-up material, in order to enable a complete computer reboot on a clean/brand-new disk. Any extra material (such as server or software) that would be required to perform these back-up (except basic file copy with standard protocols such as CIFS/SMB, FTP, CP/SFTP,NFS) must be provided by the Contractor. This is especially the case if a tool/software different from Symantec Ghost is recommended.

If the software has a protection mechanism that could interfere with an equipment disk replacement, then the Contractor must provide to CEA-LETI the way to reactivate the software. In Particular, this is mandatory if a new User License Key is required by the software after a hard drive change.

3.4 Transfer and handling of wafers

Not applicable.

3.4.1 Wafers specifications

Not applicable.

3.4.2 Load ports

Not applicable.

3.4.3 Handling and contact surfaces

Not applicable.

3.4.4 References of wafer carriers used on equipment

Not applicable.

3.4.5 Handling system reliability

Not applicable.

3.5 Mini environment

Not applicable.

3.5.1 Check of the physical characteristic of the air

Not applicable.

3.5.2 ESD (Electrostatic Discharge)

Not applicable.

3.5.3 Particle checks

Not applicable.

3.6 *Interface with the rest of the clean room and its organisation.*

Not applicable.

3.7 Contamination

Not applicable.

3.7.1 Particle contamination

Not applicable.

3.7.2 Metallic contamination

Not applicable.

3.8 *Specific interface with facilities*

Not applicable.

3.8.1 If CMP type equipment (Chemical Mechanical Polishing)

Not applicable.

3.8.2 If WET BENCH type equipment

Not applicable.

4 GENERAL BUILDING, FLUIDS, ELECTRICITY, ENVIRONMENT SPECIFICATIONS

4.1 *Environment of the equipment*

4.1.1 Building specifications

Features of the location of the equipment:

- Environment: [lab with temperature control](#).
- Cleanliness class according to **ISO 14-644-1**:
 - [Building 51B room 265: ISO 6](#)
- Environmental Conditions and tolerances (temperature and humidity)
 - **51B:** **21 +/- 2 ° C and 47 +/- 5% RH**
- Mounting: [openspace](#)
- Location of devices: [gray fingers](#)

4.1.2 Building fluids

See **Appendix B**: General fluids building 51

4.1.3 Building power network specifications

CAUTION:

The equipment covered by these specifications must be connected to an electrical distribution mains with earthed neutral system (TN –S diagram).

If necessary, refer to CEI 60364 standard

Electrical features

Power supply voltages available on main:

- Single-phase: 1 phase + neutral + earth
Phase/Neutral voltage: 230 V +/- 10 %
 - Three-phase: 3 phases + neutral + earth
Phase/Phase voltage = 400 V +/- 10 %;
Phase/Neutral voltage = 230 V +/- 10 %
- Main frequency: 50 Hz

4.1.4 Adaptation of the machine to the power network

CAUTION:

When the neutral lead is distributed in the machine, a cut-off device must be placed on the neutral lead, at the equipment item's general switch.

Neutral lead colour in machine:

Inside the equipment, the neutral lead shall be of light blue colour (EN 60204 standard) or clearly identified otherwise (colour ring, marker).

Protection lead colour in machine:

Inside the equipment, the protection lead (earth) shall be of green and yellow colour.

Power supply transformer (general machine)

Should a transformer be necessary :

- Contractor shall estimate this supply as an option, indicating all electrical features (power, primary and secondary voltages, etc.).
- A dry transformer (without liquid dielectric medium) is preferable;
For transformers or other devices, containing a liquid dielectric medium:
 - Pyralene is prohibited;
 - Installation conditions in machine shall meet Decree of January 17, 1989 establishing prevention steps against fire hazard introduced by dispersion and ignition of flammable liquid dielectric media. In this case, mandatorily consult us.
- Characteristics of the transformer:
 - It shall be compliant with the "low voltage" directive **2014/35/EC** and affixed with the CE marking for this purpose,
 - case of a three-phase transformer:
Secondary windings must be bridge connection so that there is a neutral point
This provision applies even if the neutral is not used by the machine in order to enable protection against indirect contacts (ground connection if necessary)
- For "dry" transformers, the applicable construction standards are:
 - **NF EN 61558** standard, for powers of less than 25 KVA single-phase, or 40 KVA three-phase
 - **NF EN 60076** standard, for powers in excess of 25 KVA single-phase and 40 KVA three-phase

4.1.5 Uninterruptible power supply (UPS)

Should all the equipment be powered by an emergency power supply (UPS), this power supply shall be provided by CEA.

Contractor shall provide all the necessary information for defining the product (voltage, power, autonomy).
Contractor shall provide lock terminals on the equipment to connect the emergency power supply.

If only a section of the equipment is powered by an internal UPS incorporated by the manufacturer (IT section for example), the following rules shall be complied with:

- An omnipolar separation mechanism shall be installed downstream of the UPS in order to allow maintenance operations.
- The presence of voltage after shutoff of the machine master switch shall be signalled on same.
- The circuits still powered after cut-off must be identified in orange inside the equipment as per standard **NF EN 60204**.

4.2 Management of the environment

In reference to its “Sustainable Development” initiative, CEA-LETI is working on improving its environmental performance and would like understand what its service providers and Contractors' contributions are to this regard.

Contractor shall therefore list in its offer all the initiatives that it has undertaken and / or is planning to undertake to make its business more sustainable from an environmental and social perspective. It will provide details about:

- its efforts regarding reduction in :
 - consumption of electrical and heat energy, and fluids ;
 - exhaust flows through careful design of covers and exhaust points ;
 - cooling water flow rates using an optimized calculation for heat exchangers.
- proposed fluid recycling.

The equipment must be designed so as to limit polluting emissions in the environment in particular by implementing clean technologies, segregation and treatment of effluents and waste depending on their characteristics, and reduction of the discharged quantities.

The Contractor will provide emissions evaluation:

- vapour/gaz emissions rate and liquid chemical wastes
- Actives wastes mass and volume of if possible, pollutants rate in rinsing wastes.

4.2.1 Process Cooling Water

Not applicable.

4.2.2 Exhaust and other internal equipment air systems

Not applicable.

4.2.3 Segregation of liquid effluents

Not applicable.

4.2.4 Case of DI return or recycling of ultrapure water

Not applicable.

4.2.5 Gaseous effluents

Not applicable.

4.2.6 Odours

Not applicable.

5 SAFETY

5.1 EC conformity

The supplied equipment or service shall meet the regulations in force in France.
Said regulations include the European directives transposed into French Law.

European Directives:

Compliance with the European directives applicable to the equipment is mandatory.

In particular (if applicable) :

- “Machinery” directive **2006/42/EC**
See **Appendix D**: Specifications for delivering work equipment (Compliance with European machinery directive **2006/42/EC**).
- “Electromagnetic compatibility EMC” directive **2014/30/EU**
- “Low voltage” directive **2014/35/EU**
- “ATEX” directive **2014/34/EU**
- “Pressure” directive **2014/68/EU**

The equipment shall be EC certified, a “CE marking” shall be affixed thereon and it shall be accompanied by an EC/EU declaration of conformity.

Construction standards

Compliance with harmonized European Standards (NF EN or NF EN ISO) will be favored, the application of these standards giving a presumption of conformity on the subjects concerned.

- **Risk analysis**
The various risks (mechanical, electrical, thermal, gas, chemical, radiation) shall be clearly mentioned by Contractor in its proposal.
The risk analysis will be made according to the applicable reference standard: **NF EN ISO 12100** : "Safety of machinery - General principles of design - Risk assessment and risk reduction"

These risks shall be handled :
 - in accordance with the instructions of the applicable directives:
 - in accordance with the recommendations of Paragraphs 5.2 to 5.12
- **Design of safety related parts :**
The safety functions will be designed in accordance with standard NF EN ISO 13849-1 "**Safety of machinery - Safety-related parts of control systems - Part 1: general principles of design**" for each type of hazard (mechanical / gas / thermal...)
- **Electrical equipment of machines**
The electrical equipment of machines will be designed in accordance with standard **NF EN 60204**

Reminder of technical points in relation with the regulations:

Warning :

This paragraph is aimed at attracting the manufacturers' attention to a few specific technical points which may lead to non compliance if they're not completed.

- **Energy separation device**

The equipment will be fitted with an isolation device on each energy source (electricity, pneumatic, nitrogen, etc.) that can be locked in the off position.

- **Electrical cabinets**

Electrical cabinets will have an IP2X protection index and it will only be possible to open them with a tool or a key ; the inside of the cabinet will also have an IP2X protection rating so as to avoid any risk of direct contact during maintenance operations (components / wiring)

- **Guards design**

- Protection panels:

Protection panels (guards) will be strictly designed in compliance with Machinery Directive **2006/42/EC** (See appendix F: 1.3.8 to 1.4.3)

Moreover, the following conditions shall be complied with for selecting guards:

Fixed guards:

The installation of fixed guards by manufacturer will be accepted if:

- Frequent disassembly for maintenance is not necessary
- Removal of guard is exclusively reserved to maintenance personnel by following a written instruction drawn up by manufacturer (lock out tag out of affected moving elements for example).

Moving guards:

Moving guards will be considered as all types of guards installed on hinges (doors) or not complying with the criteria of fixed guards.

- The opening of the movable protectors will have to stop the risks present behind these protectors, by means of a safety system designed in accordance with the applicable European standards.
- The opening detectors installed on movable guards will be safety components in accordance with **NF EN ISO14119**

- **Maintenance modes**

If the machinery is equipped with "maintenance" or "service" mode in which the safety systems are neutralised, these modes will be strictly designed in compliance with Directive 2006/42/EC "Selection of control or operating modes"

(See: appendix F point 1.2.5)

Consequently:

- The maintenance of the equipment should not require the direct neutralization of the detection components (interlock doors). If this neutralization is necessary it should be done via a maintenance mode accessible via a code or a key and simultaneously cause the reduction of risks (reduction of speeds, permanent control of the movements ...)
- The maintained action required to validate the movements will be of the pedal type or "dead man" safety handle.
In particular, this system will be present on the control modules ("teach pendant ") for teaching robots.

- **Fume cupboards**

In case of fume cupboards, the applicable standards are:

NF EN 14175-1, NF EN 14175-2, NF EN 14175-3, NF EN 14175-4, NF EN 14175-6, NF EN 14175-7.

Factory and onsite "type tests" shall be subject to a conformance certificate or Contractor declaration. The Contractor shall anticipate all exhaust surveillance devices, associated servomechanisms and operator information devices on equipment operating state.

5.2 Risks connected with facilities

Power supply sectioning:

A power supply-sectioning device must be designed on the equipment for each energy source of the machine

Electrical supply cut-off device:

The accessories enabling the electrical supply of all or part of the machine to be immobilised shall be supplied with the equipment (locking circuit breakers in off position).

Compressed air connection or "service" nitrogen:

When the equipment uses compressed air or nitrogen for valve, actuator and other system control, the machine must be equipped with a general shut-off valve.

This valve must include a locking system, by means of a padlock, in order to make the facilities safe for maintenance. One or more drain/purge systems must be available to dissipate the residual pneumatic energy stored in the machine after general valve shutting-off. Energy dissipation must be harmless to any exposed personnel or operators.

Presence of an uninterruptible power supply (UPS):

The instructions of Paragraph 4.1.5 shall be complied with.

The cut-off component at UPS output may be locked in "off" position.

5.3 Risks connected with fire

Automatic fire extinction system for equipment using solvents:

Equipment implementing solvents in open tray (pans, most often) must have an automatic CO2 extinction system. This system will be connected to the operation of detectors (smoke, flame, temperature, etc.) installed above open trays, but also at equipment retention trays.

DESAUTEL (or equivalent) type automatic extinction systems certified and validated by qualified authorities shall be installed with approval of the facilities department. Dry contacts shall be supplied in the building in order to report each of the following elements of information:

- System disturbance
- Fire detection (1 detector giving alarm)
- Confirmed fire detection (2 detectors giving alarm, extinction triggered)

Intrinsic equipment fire detection system:

When fire detectors are supplied with the equipment, they must be accompanied by the risk analysis leading to their installation, in such a way that the LETI is able to make decisions on the grounds for doubling said detection using existing systems in the building which are compatible with the fire systems in place. Detectors integrated into equipment shall not be connected with the fire system of the building and shall only have an action on the equipment in question and its related peripheral devices, if required.

The Contractor will specify and provide the necessary documentation relating to:

- Periodic calibration of sensors: frequency, operating mode, calibration gas used, parts to change in preventive and corrective maintenance, and any information necessary to maintain the detectors in good working order.
- Connections required on the equipment, in case of:
 - Detection alarms for different thresholds
 - Malfunctions

A list of these interlocks with the corresponding wiring diagrams will be provided.

5.4 Risks connected with chemical products

- When chemical products (solid, gaseous or liquid) are supplied by the Contractor within the framework of installing equipment, testing or any other operation, it must comply with **EC regulation 1907/2006**. It must also supply the full list of products as well as safety information sheets in French for each product. These documents must comply with European directive CLP.

The CEA-LETI shall be particularly vigilant with regard to compliance with content, pictograms and classification used, as well as the provision of a version drafted in French.

- Product classified as noxious, toxic, extremely toxic, corrosive, etc. (e.g., fluorhydric acid with a concentration greater than 7%, gas, etc.) supplied by an outside source to the equipment shall be distributed with double-walled pipe up to the equipment intake. Pipes connecting dangerous chemical fluids between the equipment and auxiliary modules will also be double-walled.
- If there is a risk in a chemical containment of the equipment during a maintenance operation, a safety device in the system shall be able to cut power supply of devices that may present a risk to personnel.

All equipment containing liquid chemicals must be organised in such a way as to create a retention system aiming at preventing the accidental spread of said products outside the equipment without voluntary action. All elements of the installation in the equipment that could be a source of leaks (fittings, valves, filters, etc ...) will be placed on the retention and under extraction.

- These retention systems shall be fitted with leak detectors reporting the information to the equipment control console. Alarm enabling of a detector shall interrupt automatic supply to the machine and the chemical fluid circulation.

The detectors shall be tested before activating the equipment.

- The operation of equipment shall be connected with the proper operation of the extraction. The extraction level shall be permanently controlled by one or several extraction controllers which will drive a visual alarm per stack light (code green, orange and red) and a sound alarm on the working station and if necessary on the concerned sub equipment). These sensors will give an indication of current negative pressure level and shall also ensure equipment safety servo mechanisms in the event of an alarm. It must be possible to recalibrate the sensors on site to correct drifts over time. A calibration certificate shall be provided upon installation.

For each type of control sensor used on the exhaust a spare sensor will be delivered with the equipment to be kept as a spare part.

- NB: for automated equipment, this “extraction” alarm may be linked with the other types of alarms on the equipment control consoles.
All equipment modules and devices (reactor, chemical vat, stove, coater, gas or chemical storage cabinet including the lower cabinets of the benches, canisters, etc.) and, more generally, any compartment where a leak may occur including those housing connections, valves, pumps, etc., that present a risk to operators shall be included in the exhaust system.
- In order to ensure efficient exhaust, the mobile front should have no rim.
Ideally, the bench should have 2 exhaust strips: a first one on the worktop level and a second one located on the top of the bench, in order to promote the exhaust of chemical vapours.
If the bench includes bulky elements (ultrasonic tank, oven, etc.), these elements must be embedded in the worktop and not on the top of it in order to prevent any perturbation of exhaust and aerolics performance.
- Chemical product trays of pans must be equipped with an adjustable time delay automatic drainage system in such a way that solutions may be automatically directed towards drains in the event of a prolonged shut-down of extraction.
- For the requirements of certain processes, chemical products will need to be heated. At the end of operation, these baths may only be evacuated to designated drains if the temperature of the bath does not reach 60°C. For higher temperatures and for drainage in the “solvent” drain, a study must be conducted in order to determine the best solution: PVDF material, dilution module, thermal exchanger, etc.

If the solution selected by the Contractor consists in installing a buffer tank to enable these effluents to cool, it must be located under retention and be equipped with an adjustable time delay drainage system as stated previously.

- For equipment with processed chambers, the Contractor must provide the list of expected by-products in the event the chamber is opened, in order to facilitate maintenance operations.
- For equipment with gas detectors, The Contractor will specify and provide the necessary documentation relating to:
 - ✓ Periodic calibration of sensors: frequency, operating mode, calibration gas used, parts to change in preventive and corrective maintenance, and any information necessary to maintain the detectors in good working order.
 - ✓ Connections required on the equipment, in case of:
 - Detection alarms for different thresholds
 - Malfunctions

A list of these interlocks with the corresponding wiring diagrams will be provided.

- For solid compounds used as insulating materials in furnaces, the Contractor will provide all relevant information on the nature and dangerousness of these materials: Material Safety Data Sheet (MSDS) should be provided. If one of these materials contains Refractory Ceramic Fibres (RCF), the Contractor must provide costed alternatives: substituents and less dangerous materials than RCF.

5.5 Risks connected with handling

For the parts of equipment requiring handling: pumping units, chamber lids, covers, etc., notably during maintenance or installation operations, lifting means must be foreseen and described in the equipment safety notice.

Systems integrated into the equipment will be favoured over mobile systems.

In the case of a mobile system, it must be marked "CE", be the subject of an EC declaration of conformity and an instruction manual in French.

5.6 Risks connected with pressurised equipment

For equipment subject to "Pressure" directive **2014/68/EU**, Contractor shall:

- Provide a complete file of the equipment in order to enable the commissioning inspection operations
- Update the roll where all the interventions will be recorded (inspections, requalification, and maintenance).

Contractor shall submit the periodicity of visit and controlled equipment requalification.

5.7 Risks connected with work at height

Should equipment use, maintenance or installation operations require elevated access, the Contractor shall provide protected access with guard rails in compliance with European standards **EN 14122-3**, if not, anchoring points compliant with European standards **EN 795**. In the latter case, technical documentation must make a very clear reference to it, in such a way as to implement related regulatory checks.

Where required, related personal protective equipment may be requested. They must be validated by the HSE Cell.

5.8 Risks connected with laser radiation

Lasers must have EC marking. The design, implementation and labelling of lasers must be compliant with standard **EN 60825**.

Should a risk exist beams must be automatically shut-off when the enclosure in which they are confined is opened (for example: opening of vacuum chamber, opening of mobile protectors, etc.).

Once completed by the Contractor, the following table should be inserted in Appendix A:

Type	Class	Continuous or pulse	Wave length	Power	Beam diameter before focusing	If pulsed laser		
						Energy	Length of pulses	Number of pulses

5.9 Risks related to sources of ionizing radiation (radioactive sources / electric generators of ionizing radiation, etc.)

If the equipment contains radioactive sources, or if it embeds an Electric Ionizing Radiation Generator, a description must absolutely be provided: type of source / characteristics / radiation / activity / kV / mA /

Please note: In this area, certain design obligations result solely from French regulations, including the decisions of the Nuclear Safety Authority (ASN)

The design of the device on the risk of ionizing radiation must meet an obligation of results, the specifications of which are given below.

Equipment design:

DECISION 2017-DC-591

The equipment must comply with DECISION 2017-DC-591 of the Nuclear Safety Authority "setting the minimum technical design rules to which the premises where electrical devices emitting X-rays are used must comply"

Full text available (in French) on request.

Warning: also applies to electrical devices emitting unwanted X-rays (for example: ion implanters, electron beam welding equipment, etc.)

In application of this decision:

- **Access restrictions**
When access is possible (door / hatch) :
 - Door open = X-ray emission not possible
 - Opening of the door = shutdown of X-ray production
- **Emergency stops**
An emergency stop button will be present near the control device and will cause:
 - A shutdown of X-ray production upon triggering
 - Holding of the stop order until it is rearmed
- **Risk light signalling:**
 - A light sign will be installed on each access
 - Power-on signalling
 - Radiation emission signalling
 - If several devices are installed: identification of the one in operation
 - In application of this criterion, a specific light tower will be installed outside the equipment at each access (doors);
 - orange color will indicate power on;
 - red color will indicate emission
- **Shutter**
 - The X-ray emission signalling will operate in connection with the position of the shutter and will flag the shutter open position.
 - In addition, a light signal will be present at the shutter level

Construction and test rules

FRENCH STANDARD NFC 74-100

Any equipment equipped with one or more X-ray generators must comply with the French standard **NFC 74-100 " RADIOLOGY EQUIPMENT X-Ray Apparatus Construction and tests REQUIREMENTS "**

The application of this standard is mandatory in France.

Certification assessment will be planned by the manufacturer on his site before delivery

If necessary please contact us to obtain the address of an accredited organization able to do this assessment.

The certificate of conformity regarding NFC 74-100 will be provided at delivery.

Radiation flux :

The manufacturer will certify that the emission measured at any point 10 cm from the equipment is less than 1μ Sv / hour (1 micro Sievert per hour)

5.10 Risks connected with noise

In reference to machinery directive **2006/42**:

“Machinery must be so designed and constructed that risks resulting from the emission of airborne noise are reduced to the lowest level taking account of technical progress and the availability of means of reducing noise in particular at source.

The level of noise emission may be assessed with reference to comparative emission data for similar machinery.”

The noise level measurements will be performed and mentioned in the instruction manual in compliance 2006/42

The noise level generated by the equipment in its installation environment should be less than 70 dB (A).

If noise level is likely to exceed 70 dB (A), the Contractor will suggest quoted technical solutions of reduction: silent hardware, soundproof materials, soundproof covers on noise sources...

5.11 Risks connected with temperature

Hot surfaces: the temperatures of directly accessible hot surfaces must comply with standard requirements **NF EN ISO 13732-1**

Cold surfaces: The temperatures of cold surfaces directly accessible shall comply with the requirements of standard **NF EN ISO 13732-3** of 2008

WARNING: In the case of heating systems embedded in the machine

- The manufacturer must foresee the consequences of a malfunction of the control unit by installing a completely independent overheating safety device (sensor / regulator ...). This safety system will shut down the power and will require manual reset for restart (after fault clearing). The reliability of the cut-off system will be defined according to **EN 13849-1**
- The manufacturer must be able to define the consequences of a sudden and simultaneous complete interruption of the machine's "facilities": water / electricity / extraction hot air / nitrogen service ... when the system is at nominal temperature.

The equipment will have to support this scenario without generating a fire risk internal to the machine, nor any other risk (explosion ...)

In this scenario, if the temperature of the external enclosure of the equipment exceeds that of the equipment in normal mode, the Contractor will give the estimated temperature values and will consider them in the installation instructions (safety distances from the walls and other equipment).

5.12 Signaling

Signalling: risks shall be indicated on the machine using danger pictograms such as described in European regulations, accompanied as the case may be by an additional text;

In this case, the text must be labelled in French.

5.13 Intervention conditions on the CEA-LETI site

In collaboration with the Contractor and its possible sub-contractors, the CEA-LETI shall draft an overall prevention plan for installation, start-up and possibly development (JDP) services on equipment.

As loaning material is prohibited at the CEA, the Contractor and any subcontractors must provide safety materials needed to prevent specific risks generated by its intervention: PPE, CPE, breathing apparatuses, etc. It shall be

responsible for replacement and repairs and, if required (without compensation on the part of CEA), it shall promote awareness and train its staff for use of equipment as per regulations. This material shall comply with regulations in force and shall be accompanied by a certificate of conformity.

The Contractor and its possible sub-contractors must provide all collective safety equipment used to prevent accidents due to works (marking work areas, marking traffic areas, marking handling and flyby areas, marking and installation of barriers around pits, level differences, etc.). It shall carry out and ensure removal of them as soon as the service no longer requires the presence of marking.

6 SUSTAINABLE DEVELOPMENT

6.1 Corporate Social Responsibility (CSR)

With an amount representing nearly 2.7 billion euros, CEA purchases are an integral part of societal and environmental issues.

The CEA monitors the quality and diversity of relations with its suppliers. It conducts a responsible purchasing policy based on three priority commitments:

- Create and maintain confidence-inspiring relations with its suppliers,
- Take into account the responsible dimension of its purchases,
- Contribute to the development of Small and Medium Enterprises (SMEs) and innovation.

Since 2004, it has been a signatory of the “responsible supplier relationship” charter and adheres to the SME Pact, a national support scheme for innovative SMEs.

The CEA's commitment to developing responsible purchasing cannot be made without taking this dimension into account by its suppliers.

The CEA is therefore counting on your proposals within the framework of this consultation to optimize the environmental impact of your services and develop the integration of people who are excluded from employment and the protected sector.

6.2 Sustainable development and development of the local economic fabric

As part of the “Sustainable Development” approach, CEA Grenoble is striving to improve its environmental performance and requires the cooperation of its suppliers in this respect.



In its proposal, the service provider shall present its corporate strategy as regards sustainable development and its specific improvement proposals concerning the work that covered by these Specifications.

Furthermore, as part of its “Plan Déplacement Entreprise” (“Corporate travel plan”), CEA Grenoble undertakes to reduce its environmental footprint.

The service provider shall cooperate with CEA Grenoble and undertakes to use zero emission vehicles as much as possible to meet the requirements mentioned in these Specifications.

Furthermore, LETI MINATEC is a pedestrian area, with regulated vehicular access.

Vehicles identified by the company's name may access the pedestrian area subject to CEA Grenoble's approval. All other vehicles shall be parked in the dedicated car park.

The recovery or disposal of waste created during the performance of the services is the responsibility of the supplier during the duration of the contract.

The supplier shall ensure that any operations, collection, transport, storage, sorting and disposal of waste created by the services subject to the contract are carried out to the sites likely to receive them, in accordance with the regulations in force.

6.3 Energy performance

As part of its ISO50001 "energy management" initiative, CEA Grenoble is working to improve its energy performance, and would like to be supported in this by its suppliers.



In its offer, the service provider presents its proposals for improvement specific to the services detailed in the present specifications.

CEA Leti asks the service provider to propose all equipment and solutions enabling to optimize and reduce as much as possible the energy consumption of the entire project, and to propose in its offer the energy saving certificates related to the project. »

7 EQUIPMENT DELIVERY CONDITIONS

The equipment and all the peripherals will be delivered clean and packaged in a serious and appropriate way. The transport platforms, pallets and packaging cases must be adapted to the weight and volumes of the elements in order to ensure safe a transport and avoid any dispute connected with improper packaging.

The following cleanliness requirements shall be fulfilled for the specific case of equipment intended to be installed in the clean rooms:

- very careful cleaning of all the subassemblies before shipment in order to remove any trace of shavings, hydrocarbons, grease or any other potential contaminant.
- packaging of the parts intended to be installed in the clean room under double film in order to perform progressive unwrapping while allowing a minimum amount of particles to contaminate the clean room. Peripherals intended to be installed in the basement may be packaged in single skin.
- likewise, all packages containing cable works, spare parts, various accessories required for assembling the equipment must be compatible with the clean rooms; wood, cardboard or traditional paper-type materials are prohibited; Contractor shall provide plastic-based non-contaminating wafer carriers (rigid or corrugated plastic cases for example).
- Filters of the environmental chambers and **FFUs shall not be delivered mounted on the equipment at delivery** to avoid any risk of particulate contamination and deterioration during handling and installation. Mounting remains the responsibility of the Contractor.

8 CONDITIONS FOR INSTALLING EQUIPMENT

Contractor shall enclose with its technical proposal the pre-installation document defined in **Appendix E**, then an installation file at the time of the installation.

It shall include all the installation conditions in particular the elements required in Paragraph 2: "instruction manual /installation" of Appendix E: Specifications pertaining to documents and manual to be provided with the equipment.

9 TRAINING & LEARNING

Not applicable.

10 DOCUMENTATION

See **Appendix E**: "Specifications relating to the documents and manuals to be supplied jointly with the equipment". Each manual must be available in two paper version plus possible CD-ROM version
From a statutory standpoint, the delivery of a document or publication in CD-ROM format only (no hardcopy version) is construed as non-conformity.

11 WARRANTY

11.1 Warranty conditions

Warranty shall start at the date of equipment acceptance for a duration of two years.

Warranty shall include corrective and preventive maintenance operations, with at least one preventive maintenance per process chamber and per year.

All costs related to maintenance operations during warranty period shall be borne by the Contractor: labour, spare parts, consumables, travels, shipments etc...

11.2 Support during warranty

During the warranty period, the Contractor agrees to provide on-site support within a maximum timeframe of 8 business hours after receiving an e-mail or a call from CEA-LETI.

Support shall be available for on-site intervention from 5am-9pm on weekdays and from 8am-5pm on week-ends.

11.3 Equipment performance indicators

- A) The definition of the down-time calculation used by the CEA-LETI is set out in Appendix C.

Up-time (%) = 100 – Down-time (%)

- B) During the warranty period:

Uptime > 90%

MTBF¹ > 1000h

MTTR² < 4h.

- C) Penalties during the warranty period

The up-time (see **Appendix C** "up-time definition") shall be assessed on a three-monthly basis.

Should one of the 2 parameters (Uptime or MTBF), recorded during the warranty period, not comply with specifications: the warranty period shall be automatically extended by a period of **3 MONTHS**.

During this extension, the Contractor shall perform all the corrective actions necessary to meet the specifications.

If, at the end of this warranty extension period, the specifications are still not met: the warranty shall be further extended by periods of 3 MONTHS until the specifications are met.

12 MAINTENANCE

12.1 Spare parts

12.1.1 List of spare parts:

In its bid, the Contractor shall include:

- A comprehensive list of spare parts;
- A comprehensive list of consumables needed to operate the equipment, with the functions, reference and price for each component.

These lists may be used as a basis for drawing up an agreement for the supply of spare parts and consumables.

The Contractor shall specify the standard delivery timeframe as well as the timeframe for an emergency situation.

12.1.2 Process-kit :

Not Applicable

¹ Mean Time Between Failure

² Mean Time To Repair

12.1.3 Storage area

Not Applicable

12.2 Maintenance contract

At the end of the warranty period, the CEA-LETI shall have the possibility of subscribing a maintenance contract. The Contractor shall commit to be able to perform preventive and corrective maintenance for each piece of Equipment after the warranty period has expired and for a minimum period of 10 years.

In the commercial proposal, the Contractor shall calculate the price of optional maintenance services, taking the following requirement levels into account:

- Full service including preventative maintenance, unlimited corrective maintenance, and all required spare parts. The Contractor should also commit to a defined up-time of the tool during this period. Unless otherwise stated, the performance of the tool during the Full Service contract will be that defined in the current « EQUIPMENT SPECIFICATIONS FORM ».
- Preventive maintenance plus corrective maintenance on request (hourly rates) complying with intervention and repair deadlines.

Further to the adjustment of CEA's needs with respect to maintenance, the maintenance contract may be implemented after the warranty period has expired further to negotiations.

12.3 Cost of ownership (COO)

Contractor shall provide the cost of ownership of system, including:

- Facilities consumption (gases, water -flows and required cooling capacity-, electricity, thermal load)
- Idle condition (includes consumables costs)
- Wafer move based (additional cost when tool is in production mode)
- Scheduled maintenance program and associated parts costs.

13 CHECKS & TESTS

The tests and checks of conformity for equipment subject of these specifications are broken down into six groups:

- ✓ At the factory
- ✓ Delivery
- ✓ Installation and commissioning
- ✓ Qualification
- ✓ Acceptance
- ✓ End of warranty

13.1 Checks and tests at the factory (Factory acceptance tests)

Not applicable

13.2 Check upon delivery & at unpacking

Contractor shall submit the packing procedure for CEA-LETI acceptance. It shall at least specify breakdown of the packages, space requirement and associated instrumentation (example: accelerometer indicator).

The Contractor will ensure proper following of this procedure. If the delivery occurs in the presence of the Contractor (or his representative), the Contractor will check the integrity of the various packages, analyse the associated instrumentation and draft a "delivery" report (using their own documentation). Otherwise, the delivery countersigned by CEA-LETI shall be considered as the delivery report.

The packages destination must be indicated on boxes: basement or clean room.

The Contractor shall ensure that the equipment is correctly unpacked.

13.3 Installation & commissioning

After uncrating completion, the equipment will be moved to its final location in the cleanroom by CEA-LETI or its subcontractor. The Contractor shall then take care of equipment final assembly and interconnections. The Contractor shall use its own tools to perform equipment assembly, including handling and lifting tools that may be necessary.

The Contractor shall attend all the operations to install and connect the equipment to the facilities (fluids, extractions, etc.) and shall make sure that the latter are compliant with the Contractor's specifications.

Prior to powering up the equipment, CEA-LETI has programmed a compliance check of the applicable safety regulations (EC instructions), this check shall be performed by an independent approved body. The Contractor must be present and provide the required documents for the assessment of the equipment.

After powering on the equipment, the Contractor will perform the startup and adjust hardware settings (robotics etc.). The Contractor will carry out checks on facilities which includes checking the various safety controls. The Contractor shall prepare and provide a "hardware report" commissioning which summarizes the progress of this step and the result of the various controls. This report will confirm that the connection by the Contractor and standard safety tests are completed. The main safety elements concerned are: emergency stops, the extraction detection, leakage or gas detection, door contacts ... (Operation and connections)

At this stage, the CEA-LETI will arrange for a safety compliance inspection by the applicable regulatory compliance body (EC requirements). This check is performed by an independent accredited body. The Contractor will be present during this inspection and will make all necessary documents available for the assessment of the equipment. Anomalies and malfunctions will be promptly corrected by the Contractor no additional costs. Depending on the anomalies, CEA-LETI may decide to suspend the commissioning operations pending remediation of the problems. Non-conformities noted correspond to non-compliance with the regulatory points. Any non-compliance must be resolved before the acceptance report can be signed.

The fluid connections to the equipment (process or chemical gases) will be made by CEA-LETI after receiving the "hardware report" described above from the Contractor and after the safety compliance inspection described above has been successfully completed.

The CEA-LETI also employs a firm that tests exhaust efficiency and air flow (FFUs) and takes ESD measurements.

For all the fluid connections (including effluents) or gas inter equipment or modules provided by the Contractor, the latter will carry out the marking and direction of these networks in accordance with European standard NF X 08-100 including pictograms SGH informing of the danger by printed solvent resistant laminated polyester adhesive stickers. The valves will be equipped with color labels engraved out of PVC 8/10e fixed by adapted collars indicating their function.

At the end of the installation, the Contractor will remove all waste and parts from the installation which are no longer required.

13.4 Qualification

Contractor shall submit the qualification procedure to CEA-LETI for acceptance. It shall check all the functional specifications described in Paragraph 2.

This qualification procedure shall be performed in the presence of CEA-LETI authorised representatives.

The summary of these tests shall be countersigned by CEA-LETI (qualification summary report).

13.5 Acceptance

This acceptance recognises conformity of the equipment and transfer of ownership. The equipment warranty period shall start once the acceptance has been confirmed.

Acceptance shall be pronounced after:

- ✓ Full delivery of the equipment
- ✓ The end of the installation and commissioning operations
- ✓ The qualification checks and tests successfully passed
- ✓ EC conformity approval given by the body accredited by CEA.
- ✓ Authorisation from the installation manager at the home site
- ✓ Delivery of the documentation (see make up in APPENDIX E: Specifications pertaining to documents and manuals to be supplied with the equipment)

A reception document without qualifications (*) will be signed between CEA-LETI and Contractor.

(*) A concession may possibly be granted for a reserve forming the subject of a detailed action plan for restoring compliance to the specifications subject of this document. If so, acceptance will be pronounced "with reservations"

Note: Only the report in CEA-LETI format, shall prevail to assert the associated payments with this stage and launch the warranty period.

13.6 End of warranty

The completion of the guarantee is pronounced at the end of the guarantee period under the following conditions:

- ✓ Total removal of all qualifications noted during the acceptance
- ✓ No abnormalities detected
- ✓ Compliance of the equipment with the specifications during this period.

In case of any abnormality, the Contractor will perform any work required to ensure the compliance of the equipment. If the functioning of the equipment is not satisfactory, the warranty period is automatically extended by a period described in the contract.

14 INSTALLATION PREPARATION SCHEDULE

The schedule below includes the key stages of the contract. For some the date is stipulated by CEA-LETI relatively with respect to the contract starting date (T0) or the delivery date (TL), for others, the contractual date will be specified in the Manufacturer's offer.

Note: For equipment delivered in several stages, a schedule per subassembly shall be drawn up (one subassembly per delivery).

1	Starting Date The start date of the contract ("T0") is date of the acknowledgment of receiving the contract if the latter does not exceed 10 days after the date of signature of the contract by CEA. In the case of an acknowledgment received after this period the "T0" is arbitrarily set at the date of dispatch of the contract by CEA-LETI (the date of the covering letter) plus 10 days.	T0
2	Preparation file of equipment installation (Made up at least from the "installation" chapter of the instruction manual defined in Appendix E)	T0 + 0.5 months

3	Kick-off meeting at the latest 1 month calendar after notification of the order to the service provider	T0 + 1 months
4	PID (Piping and Instrumentation Diagram) approval by the Contractor. Hook Up and Fit Up will start after the official validation of PID by the Contractor	T0 + 1.5 months
5	Appendix H with definitive information relating to the required sub-equipment (to be provided by the contractor)	At the latest T0 + 2 months
6	Preparation file for equipment installation for approval; composed at least of: ✓ “Handling”, “assembly”, “commissioning and adjustments” chapters of the instruction manual defined in Appendix E. ✓ Transport specifications ✓ “Factory acceptance” and “Qualification” procedures	TL - 2 months
7	Factory acceptance (on Contractor’s site) (Prior written call of CEA-LETI representatives three weeks before). The factory acceptance file recording the checks and tests performed shall be forwarded to CEA-LETI within 10 days after the end of factory acceptance and at least 15 days before delivery.	At the latest TL - 1 month
8	Project maintenance manual in electronic format (composition of a file as per Appendix E)	TL - 0.5 months
9	Detailed programming of delivery (date, time, carriers, civil status of the workers on-site, etc). Note: Drafting of a prevention plan as per French regulation with a CEA-LETI engineer must be taken into account in the delivery schedule. The complete or simplified prevention plan (depending on the number of companies and the number of hours) must integrate commissioning of the equipment	TL - 0.5 months
10	Delivery	TL
11	Installation and assembly of the equipment and connection to the various networks Note: Given that at this stage the equipment is still the property of the Contractor (under CEA-LETI responsibility) the presence of one of its representative is mandatory during the handling and connection operations.	
12	Commissioning. This phase will be finalised with acceptance by CEA-LETI of the equipment filed formalised on a report with safety inspection of the installation.	
13	Qualification of the equipment	
14	Final equipment file (in electronic format and in two hard copies of which at least one in clean room compatible paper composed as per Appendix E)	15 days before acceptance
15	Acceptance of the equipment (This stage notifies transfer of ownership of equipment to CEA, the warranty period starts at this date)	
16	End of warranty (this stage notifies end of the equipment warranty and start of any maintenance contracts)	At the end of the warranty period and after lifting of reservation

15 APPENDICES

APPENDIX A: Summary of Contractor's comments

Use the following template and ask the Contractor to fill it:

[APPENDIX A Equipment specification.dotx](#)

APPENDIX B: or general fluids to building

GENERAL FLUIDS IN BUILDING 51B Clean Room

General fluid distribution	Building 51C characteristics	Specific observations
Cooling Water (recommended dimensionning velocity in the tube including in the exchanges : 1, 5m/s)	Material: PVC – Inox 316	Closed loop recycled water circuits → wastes water consumption prohibited Processing products : pH control corrosion inhibition, bioacide
	Outgoing pressure: 6 ± 1bars	
	Return pressure: ~ 0 bar	
	Outgoing temperature : 19 ±1 °C	
	Conductivity: 200 µS/cm ± 50 µS/cm	
De Ionized Water (recommended dimensionning velocity 1,5m/s)	pH: 7	EDI recycling of machines out let dealt with on a case by case basics depending on the risk analysis (chemical or particles pollution)
	Material: PVDF-HP	
	Pressure: 5 +/-0.5 bar	
	Temperature: 20°C +/-1°C	
	Resistivity: 15 Mohm.cm	
City Water	pH: 7	SIE/EXP
	Particles < 50 /l @ 0.2 microns	
	Material: PVC	
	Pressure: 6 bar	
	Temperature : 12°C to 16°C	
Process Vacuum	Conductivity: 450 µS/cm	
	pH: 7.7	
	Calcium: 70 mg/l	
Nitrogen gas "service" (recommended dimensionning velocity 20 m/s)	Material: PVC-U	Service nitrogen replace compressed air for all pneumatic uses: it is also used for vacuum pump ballasting.
	Relative pressure: ~ -880 mbar	
	Material: stainless steel 316L Ra 0.8	
	Relative pressure: 7 +/-0.5 bar	
Nitrogen gas "process" (recommended dimensionning velocity 20 m/s)	O ₂ < 1000 ppb	The nitrogen "process" is used for all which concerns the processes: purges, sweepings(scannings) of sieve(airlock,sieves,airlocks), ...
	H ₂ O < 1000 ppb	
	Material : stainless steel 316L Ra 0,4	
	Relative pressure: 7 ± 0.5 bars	
	O ₂ < 10 ppb	
Nitrogen Liquid	CO + CO ₂ + C _n H _m < 100 ppb	Max capacity 1Nm3/h
	H ₂ O < 10 ppb	
	H ₂ < 10 ppb	
	Material: stainless steel 316L Ra 0,4	
Compressed Dry Air	Purity ≥ 99.995	
	O ₂ ≤ 5 ppm	
	Humidity ≤ 5 ppm	
	Material: stainless steel 304L	
	Relative pressure: 7 +/-0.3 bar	
General fluid distribution	H ₂ O < 2 ppm	
	Temperature: 20°C +/-5°C	
	Particles 0.2 microns< 2 /cubic ft	
	Building 52C characteristics	
Network argon (recommended dimensionning velocity 20 m/s)	Material: stainless steel 316L Ra 0,4	
	Relative pressure : 6 bars	
	O ₂ < 100 ppb	
	N ₂ < 100 ppb	
	H ₂ O < 100 ppb	
	H ₂ < 100 ppb	
	CO ₂ < 50 ppb	

	C _n H _m < 100 ppb	
Oxygen network	Material: : stainless steel 316L Ra 0,4	
	Relative pressure : 8 bars	
	H ₂ < 50 ppb	
	N ₂ < 100 ppb	
	CO ₂ < 100 ppb	
	CH ₄ < 100 ppb	
Helium network	Material: stainless steel 316L Ra 0,2	
	Relative pressure : 5,5 bars	
	O ₂ < 10 ppb	
	N ₂ < 100 ppb	
	H ₂ O < 20 ppb	
	CO ₃ CO ₂ < 50 ppb	
	H ₂ < 100 ppb	
	THC < 50 ppb	
Hydrogen network	Material: stainless steel 316L Ra 0,2	
	Relative pressure : 4,5 bars	
	O ₂ < 100 ppb	
	N ₂ < 200 ppb	
	H ₂ O < 20 ppb	
	CO ₃ CO ₂ < 50 ppb	
	THC < 50 ppb	
Waste collection	Building 51C characteristics	Specific observations
Acid-base drain	Material : PP	Reprocessed locally in a neutralizing plant - imperative limitation of discharge temperature at tool outlet --> less than 60°C
Fluorinated drain	Material : PP	Collected in a tank for reprocessing off site - imperative limitation of discharge temperature at tool outlet --> less than 60°C - limitation of dilution to reduce the volumes to be reprocessed : concentration > 1% --> no water venturi system but rather gravity draining.
Solvent drain	Material : stainless steel	Collected in a tank for reprocessing off site - limitation of dilution to reduce the volumes to be reprocessed --> no water venturi system but rather gravity draining or air venturi system.
Waste water drain	Material : PVC	

Ventilation / extractions	Building 51C characteristics	Specific observations
Therm recovery network	Material: Jacob-type flanged RS stainless steel jacket. Available negative pressure: from -200 to -300Pa equipment inlet depending on location	Aeraulic network dimensioning in equipment for air velocity $\leq 8\text{m/s}$ stainless steel flexible jacket accepted for limited use (<1ml). Aluminium prohibited
Acid-base recovery network	Material: M1 PVC Available negative pressure: from -200 to -300Pa equipment inlet depending on location	Aeraulic network dimensioning in equipment for air velocity $\leq 8\text{m/s}$ M1 flexible jacket with smooth inside accepted for limited use (<1ml)
Solvent recovery network	Material: Jacob type flanged RS stainless steel jacket. Available negative pressure: from -200 to -300Pa equipment inlet depending on location	Aeraulic network dimensioning in equipment for air velocity $\leq 8\text{m/s}$ stainless steel flexible jacket accepted for limited use (<1ml). Aluminium prohibited
Vacuum pump recovery networks	Material: rolled and welded stainless steel jacket Negative pressure: from -800 to -1000Pa depending on location	Removable networks with Pneurop-type quick-disconnect clamp for cleaning
Laminar flow for blowing in equipment	Fan Filter Unit to be provided for by Contractor	Installation must comply with EN ISO 14644 standard with easily removable filters.
Treated air Building 52C	Temperature: $21^{\circ}\text{C} \pm 1$ Humidity: $47\% \pm 5$	Operating limits: Outside weather conditions: Winter -12°C , RH = 90% summer: $+32^{\circ}\text{C}$, RH = 40%

APPENDIX C: Definition of Availability

1. Planned time

The total planned time corresponds to the total hours of use for a reference period: 5 shifts - 7 days (168h/week).

2. Up-time definition

The basic formula for calculating the up-time is:

- Up-time (%) = 100 - Equipment down-time (%)

3. Down-time definition

The equipment down-time is the time during which the machine cannot be used for production according to the process specifications.

The equipment down-time is divided into:

- Scheduled down-time
- Unscheduled down-time

A) SCHEDULED DOWN-TIME

The scheduled down-time is the equipment shut-down time scheduled by the maintenance and production for preventive maintenance, for operations involving cleaning, modification, improvement, changing location, etc...

B) UNSCHEDULED DOWN-TIME

The unscheduled down-time is an unscheduled period during which the machine can not be used for production. Down-time must result from a failure proper to the equipment and not result from external elements (fluids, building, etc...).

This time does not take the user's imperfections into account :

- malfunctioning after incorrect use of the equipment (non-compliance with operating procedures),
- malfunctions resulting from the user's installations or structural or social problems.

4. Measuring up-time

Due to the up-time definition given above, measuring the up-time simply involves measuring the down-time.

5. Measuring down-time

A) START

Down-time starts from stoppage of production due to stopping of the machine, either deliberate or not, and from the agreement between the production and maintenance teams that production can no longer be performed with the specifications.

This moment is recorded on a document or in a file and is immediately notified to the Contractor (in case of failure) by telephone with confirmation by MAIL within 24h.

B) DURATION

Down-time covers:

- The initial period during which the operator performs troubleshooting to locate the cause of error, plus the waiting time of a maintenance person after a call to the Contractor's departments (in the case of a failure).
- The duration of the maintenance operation (repair / improvement / modification).
- The repair time resulting from waiting for spare parts.
- The time, after repair, to burn-in and check the equipment.
- The maintenance and process qualification time.

These different times must be noted and recorded accurately.

C) END

The end of equipment down-time takes place after the process has been qualified again. At this moment the machine is again in compliance with the specifications and can be used for production in agreement with the maintenance and process teams.

The different down-time states and times are consultable and can be supplied to the equipment Contractor on request from him.

MTBF definition

The MTBF is the mean up-time value in hours between two failure (the interrupt can be scheduled or unscheduled down-time). This mean value is calculated over 13 weeks and is the number of hours of up-time divided by the number of interrupts.

$MTBF = \text{Up-time (in hours)} / \text{number of interrupts}$.

MTTR definition

Mean time to recover: mean time to put the machine back into a state of compliance, this state takes account of scheduled and unscheduled down-time and is averaged over 13 weeks.

$MTTR = \text{number of hours of down-time} / \text{number of interrupts}$

APPENDIX D: Specification for delivery of equipment subject to the European “machinery” Directive 2006/42/CE

Purpose: The aim of this document is to recall the application conditions of this directive as well as certain important technical points

1/ Reminder of the applicable regulation

The “machinery” directive is a European text transposed into the French law.

2/ Definition of a machine

A machine is “an assembly fitted with or intended to be fitted with a drive system other than directly applied human or animal effort consisting of linked parts or components, at least one of which move and which are joined together for a specific application...”

Consequently:

Any equipment complying with the definition will be designed and built in application with the “machinery” directive 2006/42

A machine is considered as “placed on the market for the first time”, “new” or “in the new condition” if it has not been used in a member state of the European Economic Community (EEC).

Consequently:

A second-hand machine from a non-EC country will be considered as new upon its entry into the EC.

The applicable regulation will be that in force at its date of entry.

3/ Reference standards

The presumption of conformity with regulatory requirements is provided by compliance with the provisions described in the harmonised standards mentioned above and circulated by AFNOR Tour de l'Europe 92049 Paris Cedex 7, France:

- specific standards to machinery
- general safety standards,
- standards pertaining to electrical equipment of machinery NF EN 60-204

Note: Compliance with standard 61010-1 does not give a presumption of compliance to the machinery directive

4/ Documents to be provided with the equipment subject to directive 2006/42

➤ **EC declaration of conformity**

2006/42 annex II:

“EC DECLARATION OF CONFORMITY OF THE MACHINERY

The declaration and translation thereof must be drawn up under the same conditions as the instructions [See Annexe I, Section 1.7.4.1, points a) and b)] and must be typewritten or else handwritten in capitals.

This declaration relates exclusively to the machinery in the state in which it was placed on the market and excludes components which are added and/or operations carried out subsequently by the final user.

The EC declaration of conformity must contain the following particulars:

- 1) business name and full address of the manufacturer and, where appropriate, its authorised representative;
- 2) the name and address of the person authorised to compile the technical file, who must be established in the community;
- 3) description and identification of the machinery, including generic denomination, function, model, type, serial number and commercial name;
- 4) a sentence expressly declaring that the machinery fulfilled all the relevant provisions of this directive and where appropriate a similar sentence declaring the conformity with other directives and/or relevant provisions with which the machinery complies. These references must be those of the text published in the official journal of the European Union;
- 5) where appropriate, the name, address and identification number of the notified body which carried out the EC type-examination referred to in Annexe IX and the number of the EC type-examination certificate;
- 6) where appropriate, the name, address and identification number of the notified body which approved the full quality assurance system referred to in Annexe X;
- 7) where appropriate, a reference to the harmonised standard used as referred to in Article 7, Paragraph 2;
- 8) where appropriate, the reference to other technical standards and specifications used;
- 9) the place and date of the declaration;
- 10) identification and signature of the person empowered to draw up the declaration on behalf of the manufacturer or his authorised representative.”

➤ **An instruction manual**

An instruction manual shall be drawn up in compliance with Paragraph 1.7.4 of Directive 2006/42; see our Appendix E

5/ Marking on the equipment (2006/42 – 1.7.3)

“I. – Each machinery must be marked visibly, legibly and indelibly with the following minimum particulars:

- a) The business and full address of the manufacturer;
- b) Designation of the machinery;
- c) The CE marking;
- d) The designation of series or type;
- e) The serial number if any;
- f) The year of construction, that is, the year in which the manufacturing process is completed. It is prohibited to predate or postdate the machinery when affixing the CE marking.

Furthermore, machinery designed and constructed for use in a potentially explosive atmosphere must be marked accordingly.

II. – Machinery must bear full information relevant to its type and essential for safe use. Such information is subject to the requirement set out in Section 1.7.1.

III. – Where a machine part must be handled during use with lifting equipment, it must be indicated legibly, indelibly and unambiguously.”

APPENDIX E: Specification relating to documents and manuals to be provided with the equipment

1. Purpose

This appendix is intended to define the documentation to be delivered by the Contractor with the equipment (content, language, delivery schedule).

The documentation to be delivered by the equipment must meet current regulations.

The CEA-LETI / LETI specifications include the statutory requirements.

These obligations depend on whether the equipment is subject to the machine directive 2006/42 / EC.

2. Supply of an equipment item subject to machinery directive 2006/42/EC (e.g. 98/37/EC)

2.1. Regulatory obligations

2.1.1. Instruction manuals

The regulations describe all the elements relating to the instructions that must be supplied with the equipment (content, language etc.).

This information is included in Annex I to Directive 2006/42 transposed into French law (Annex I of Book II of the Labour Code)

Content

The instruction manual will be drafted in compliance with Paragraph 1.7.4. of this appendix and where applicable Paragraphs 3.6.3 (moving machines) and 4.4 (lifting systems).

2006/42 - 1.7.4 .2: Content of the instruction manual:

"Each instruction manual must contain, where applicable at least the following information:

- a) The business name and full addresses of the manufacturer;
- b) The designation of the machinery as marked on the machinery itself except for the serial number in compliance with Paragraph 1.7.3;
- c) The EC declaration of conformity or a document setting out the contents of the EC declaration of conformity, showing the particulars of the machinery, not necessarily including the serial number and the signature;
- d) General description of the machinery;
- e) The drawings, diagrams, descriptions and explanations necessary for the use, maintenance and repair of the machinery and for checking its correct functioning;
- f) A description of the workstation(s) likely to be occupied by operator;
- g) A description of the intended use of the machinery;
- h) Warnings concerning ways in which machinery must not be used that experience has shown might occur;
- i) Assembly, installation and connection instructions, including drawings, diagrams and the means of attachment and the designation of the chassis or installation on which the machinery is to be mounted;
- j) The instructions relating to installation and assembly for reducing noise or vibration;
- k) The instructions for putting into service and use of the machinery and, if necessary instructions for the training of operator;

- l) The information about the residual risks that remain despite the inherent safe design measures, safe-guarding and complementary protective measures adopted;
- m) Instructions on the protective measures to be taken by the users, including, where appropriate, the personal protective equipment to be provided;
- n) The essential characteristics of tools which may be fitted to the machinery;
- o) The conditions in which the machinery meets the requirement of stability during use, transportation, assembly, dismantling when out of service, testing or foreseeable breakdown;
- p) Instructions with a view to ensuring that transport, handling and storage operations can be made safely, giving the mass of the machinery and of its various parts where these are regularly to be transported separately;
- q) The operating method to be followed in the event of accident or breakdown; if a blockage is likely to occur, the operating method to be followed so as to enable the equipment to be safely unblocked;
- r) The description of the adjustment and maintenance operations that should be carried out by the user and the preventive maintenance measures that should be observed;
- s) Instructions designed to enable adjustment and maintenance to be carried out safely, including the protective measures that should be taken during these operations;
- t) The specifications of the spare parts to be used, when these affect the health and safety of operators;
- u) The following information on airborne noise emissions:
- the A – weighted emission sound pressure level at workstations, where this exceeds 70 dB (A); if this level is less than or equal to 70 dB (A), this fact must be indicated;
 - the peak C - weighted instantaneous sound pressure value at workstations where this exceeds 63 Pa (130 dB in relation to 20 µPa);
 - the A – weighted sound power level emitted by the machinery, where the A – weighted emission sound pressure level at workstations exceeds 80 dB (A)."

Language

"All machinery must be accompanied by instructions in French.

The instructions manual accompanying the machinery must be either an original instruction manual or a translation of the original manual in which case, the translation must be accompanied by the original instruction manual."
(Transposition of 2006/42 1.7.4)

"The instruction manual is drafted in French and may be in one or more official Community languages. The word original instruction manual must appear on the language version(s) verified by the manufacturer. Where no original instruction manual exists in French, a translation into this language must be provided by the manufacturer or by the person bringing the machinery into France. This translation must bear the words translation of the original instruction manual." **(Transposition of 2006/42 1.7.4.1)**

Consequently, the following will be provided:

- The instruction manual in its original version drafted in one of the EC languages, in any case
- The instruction manual translated in French (if the original version was drafted in another language than French) in the case where this obligation is incumbent upon the Contractor.

2.1.2. Maintenance manual

“By way of exception, the maintenance instructions intended for use by specialised personnel mandated by the manufacturer may be supplied in only one community language which the specialised personnel understand.”
(2006/42- 1.7.4)

2.2. Specific specifications at CEA/LETI

Contractor shall mandatorily provide:

- The instruction manual as described in 2.1.1 and specified in 2.2.1.
- The maintenance manual as described in 2.2.2.
- A file of all elements that were tested and validated during startup and adjustments made in connection with facilities for each fluid. This file will also include factory tests and calculation sheet for parts of the facility used for their selection during design (heat exchangers, flow rates, sections of pipes that are inside equipment).
- These instructions should be delivered with the equipment except the installation section of the instructions which should be received by CEA-LETI / LETI, together with the Contractor's offer.

2.2.1. Instruction manual

The instruction manual shall correspond to the machine delivered and contain in particular the following chapters:

- Handling
- Assembly – Disassembly
- Installation
- Commissioning
- Adjustment
- Use
- Maintenance (1st level)

Handling

This chapter shall deal with the conditions for handling the equipment: lifting or bearing points, miscellaneous precautions to be taken during handling. It shall give indispensable information such as the weight in kilograms. It shall highlight the counter-indications such as for example shocks, tilting etc...

If the equipment is comprised of different parts, the same information shall be given for handling each part.

Assembly - Disassembly

This chapter shall specify if applicable the order of the operations, the precautions to be taken, and the tooling required.

Installation

This part shall contain all the specifications necessary for installation and connection of the machine on the CEA-LETI premises. A copy of this part shall be sent to the CEA/LETI/Department concerned, before the equipment is delivered. This chapter shall contain in particular the following information :

- For the equipment and its sub-assemblies: dimensions in mm, weight (in kg), dimensional drawing mentioning the connection points to the different networks.
- Environment required: dust content, hygrometry, vibrations, sensitivity to vibrations and electromagnetic radiation, extractions to be provided etc...
- Nature of the floor: resistance required with respect to the weight of the machine, flatness.
- Electricity: Voltage, Power, features of the power supply transformer if applicable.
- Pneumatics (compressed air): pressure, quality.
- Fluids: Type, pressure, flowrate, temperature, characteristics.
- Gas: Type, pressure, quality.
- Counter-indications for installation, nuisances introduced by the equipment.

All these parameters shall be accompanied by a tolerance.

Commissioning

Even if commissioning is performed by the Contractor, this chapter shall set out the procedure to be followed for commissioning of the equipment (prior checks, start-up procedure etc.).

Adjustments

A procedure shall be provided to perform tuning/adjustments within the scope of normal everyday use of the machine.

Use

This chapter shall contain:

- The conditions of use scheduled by the manufacturer.
- The definition of the workstation(s) occupied by the operator(s).
- A presentation of the equipment enabling identification of the different parts (photos, diagrams) explaining the function of each part, particularly of the control and safety means.
- A description of the running sequence of the operations performed by the equipment. All the processes available on the equipment shall be described along with the nature and influence of each "process" parameter.
- An operating mode describing the details of the operations to be performed to process a sample, a batch (for example). It shall contain the learning instructions.

CAUTION

In the case of an automatic machine, the operation mode shall not be limited to necessarily succinct description of loading/unloading of a sample or a batch (for example) but shall enable the parameters of the standard functions to be adjusted and the alarm messages to be understood.

In the case where man/machine dialogue takes place via keyboard + monitor or touch-sensitive screen, the following information provided by the manual shall enable :

- the general software architecture (maintenance part / engineering part / operator part for example) to be understood,
- navigation between the different parts,
- the parameters of a task performed by the machine and influencing the "process" (for example: speed, time, pressure, power etc.) to be adjusted, these operations falling within the scope of normal use of the machine in a research environment,
- the results or "process" running monitoring tables to be accessed,
- the alarm messages to be understood and interpreted.

To achieve this result, the manual shall reproduce the main tables displayed on the monitor. Each table shall be accompanied by comments on the actions to be performed, on the nature of the information given.

Maintenance

The object of this chapter is to enable troubleshooting to be performed and certain problems of low complexity to be resolved. It involves 1st level maintenance.

CAUTION

All the chapters of this manual shall be drafted integrating the safety warnings so that the operations described can be carried out without any risks.

This appendix is fully applicable even if supply of the equipment is accompanied by personnel training.

The potential users of this manual are technicians or engineers in charge of tuning the "processes". This shall be taken into account in the choice of the information supplied.

The equipment shall only be accepted after a detailed examination of the documents provided.

2.2.2. Maintenance manual

It shall contain :

- a presentation of the machine enabling the component parts to be located (photos),

- the interconnection diagrams between the different sub-assemblies,
- the electrical power diagrams, control diagrams, and interconnection diagrams between the different parts, the printed circuit board diagrams,
- the diagrams of the pneumatic and hydraulic circuits,
- the mechanical construction drawings (exploded views),
- the spare parts list,
- the specific documentation of apparatuses integrated in the machine such as automatic controllers, regulators, RF and micro-wave generators.
- the programs and programming tools associated to automatic controllers,
- the list of periodic checks to be performed,
- the list of preventive maintenance operations to be performed with the list of consumables associated with the operation,
- a troubleshooting guide,
- the access modes to the software maintenance parts, if applicable, and the back-up procedures.

3. Supply of equipment not subject to the machinery directive: Specifications of CEA/LETI

The special specifications of CEA/LETI [(§ 2.2)] of this document apply.

APPENDIX F: Selection of protection against risks connected with moving parts Characteristics required for guards and protective devices

Abstract of machinery directive 2006/42

1.2.5. Selection of control or operating modes

The control or operating mode selected must override all other control or operating modes, with the exception of the emergency stop.

If machinery has been designed and constructed to allow its use in several control or operating modes requiring different protective measures and/or work procedures, it must be fitted with a mode selector which can be locked in each position. Each position of the selector must be clearly identifiable and must correspond to a single operating or control mode.

The selector may be replaced by another selection method which restricts the use of certain functions of the machinery to certain categories of operator.

If, for certain operations, the machinery must be able to operate with a guard displaced or removed and/or a protective device disabled, the control or operating mode selector must simultaneously:

- disable all other control or operating modes,
- permit operation of hazardous functions only by control devices requiring sustained action,
- permit the operation of hazardous functions only in reduced risk conditions while preventing hazards from linked sequences,
- prevent any operation of hazardous functions by voluntary or involuntary action on the machine's sensors.

If these four conditions cannot be fulfilled simultaneously, the control or operating mode selector must activate other protective measures designed and constructed to ensure a safe intervention zone.

In addition, the operator must be able to control operation of the parts he is working on from the adjustment point.

1.3.8. Choice of protection against risks arising from moving parts

Guards or protective devices designed to protect against risks arising from moving parts must be selected on the basis of the type of risk. The following guidelines must be used to help to make the choice.

1.3.8.1. Moving transmission parts

Guards designed to protect persons against the hazards generated by moving transmission parts must be:

- either fixed guards as referred to in section 1.4.2.1, or
- interlocking movable guards as referred to in section 1.4.2.2.

Interlocking movable guards should be used where frequent access is envisaged.

1.3.8.2. Moving parts involved in the process.

Guards or protective devices designed to protect persons against the hazards generated by moving parts involved in the process must be:

- either fixed guards as refer to in Section 1.4.2.1, or
- interlocking movable guards as refer to in Section 1.4.2.2, or;
- protective devices as refer to in Section 1.4.3, or
- a combination of the above.

However, when certain moving parts directly involved in the process cannot be made completely inaccessible during operation owing to operations requiring operator intervention, such parts must be fitted with:

- fixed guards or interlocking movable guards preventing access to those sections of the parts that are not used in the work;

and

- adjustable guards as referred to in Section 1.4.2.3 restricting access to those sections of the moving parts where access is necessary.

1.3.9. Risks of uncontrolled movements.

When a part of the machinery has been stopped, any drift away from the stopping position, for whatever reason other than action on the control devices, must be prevented or must be such that it does not present a hazard.

1.4. Required characteristics of guards and protective devices.

1.4.1. General requirements.

Guards and protective devices must:

- be of robust construction;
- be securely held in place;
- not give rise to any additional hazard;
- not be easy to bypass or render non-operational;
- be located at an adequate distance from the danger zone;
- cause minimum obstruction to the view of the production process;
- enable essential work to be carried out on the installation and/or replacement of tools and for maintenance purposes by restricting access exclusively to the area where the work has to be done, if possible without the guard having to be removed or the protective device having to be disabled.

In addition, guards must, where possible protect against the ejection or falling of materials or objects and against emission generated by the machinery.

1.4.2 Special requirement for guards

1.4.2.1. Fixed guards.

Fixed guards must be fixed by systems that can be opened or removed only with tools.

Their firing systems must remain attached to the guards or to the machinery when the guards are removed.

Where possible, guards must be incapable of remaining in place without their attachment.

1.4.2.2. Interlocking movable guards.

1 Interlocking movable guards must be designed and constructed:

- to remain attached where possible to the machinery when opened;
- they can be adjusted only by means of an intentional action.

2 Interlocking movable guards must associated with an interlocking device that:

- prevents the start of hazardous machinery functions until they are closed,

And

- gives a stop command whenever they are no longer closed.

3 Where it is possible for an operator to reach the danger zone before the risk due to the hazardous machinery function has ceased, movable guards must be associated with a guard locking device in addition to an interlocking device that:

- prevents the start of hazardous machinery functions until the guard is closed and locked,

And

- keeps the guard closed and locked until the risk of injury from the hazardous machinery functions has ceased.

4 Interlocking movable guards must be designed in such a way that the absence or failure of one of their components prevent starting or stops the hazardous machinery functions.

1.4.2.3. Adjustable guards restricting access.

Adjustable guards restricting access to those areas of the moving parts strictly necessary for the work must be:

- adjustable manually or automatically, depending on the type of work involved;
- readily adjustable without the use of tools.

1.4.3. Special requirements for protective devices.

Protective devices must be designed and incorporated into the control system in such a way that:

- moving parts cannot start up while they are within the operator's reach;

- persons cannot reach moving parts while the parts are moving,

And

- the absence or failure of one of their components prevents starting or stops the moving parts.

Protective devices must be adjustable only by means of an intentional action.

APPENDIX G: Transfer and handling of wafers

1 – Applicable SEMI standards

Equipment must be compliant with following SEMI Standards:

	<i>SEMI Standard</i>
G1.1	SEMI E15.1 — Specification for 300 mm Tool Load Port
G1.2	SEMI E47.1 — Provisional Mechanical Specification for Boxes and Pods Used to Transport and Store 300 mm Wafers
G1.3	SEMI E57 — Mechanical Specification for Kinematic Couplings Used to Align and Support 300 mm Wafer Carriers
G1.4	SEMI E62 — Provisional Specification for 300 mm Front-Opening Interface Mechanical Standard (FIMS)
G1.5	SEMI E63 — Mechanical Specification for 300 mm Box Opener/Loader to Tool Standard (BOLTS-M) Interface
G1.6	SEMI E64 — Specification for 300 mm Cart to SEMI E15.1 Docking Interface Port
G1.7	SEMI E72 — Specification and Guide for 300 mm Equipment Footprint, Height, and Weight
G1.8	SEMI E103 — Provisional Mechanical Specification for a 300 mm Single-Wafer Box System that Emulates a FOUP
G1.9	SEMI E110 - Guideline for Indicator Placement Zone and Switch Placement Volume of Load Port Operation Interface for 300 mm Load Ports
G1.10	SEMI E111 - Provisional Mechanical Specification for a 150 mm Reticle SMIF Pod (RSP150) Used to Transport and Store a 6 Inch Reticle. (if applicable)

Other applicable standards

- Classification of air cleanliness: standard ISO 14644-1
- Metrology and test methods: standard ISO 14644-3
- Protection of electronic devices against electrostatic discharges: IEC 61340-5-1
- Mini-environment : IEST- RP-CC028.1
- Control of mini-environments: QM 07.08.011
- Check of mini-environments: QII 07.08.004
- Particle inspection of the air: QM 07.08.001
- Metrological inspections: QM 07.08.004

2. Handling Device

Loadport:

	<i>Loadport</i>	<i>Objective</i>
G2.1	Loadport Kinematic coupling pins ground resistivity value	< 100 kohm
G2.2	Maximum wafer insertion temperature in FOUP	< 100 °C
G2.3	Maximum FOUP environment continuous temperature	80°C
G2.4	Inserted wafers in FOUPs are dry	No droplet
G2.5	Maximum static charge during wafers FOUPs insertion	< 100V cm
G2.6	Maximum delay between docking request and end docking movement	< 10s
G2.8	A “load” push button (one position stable) is placed at the right front side of FOUP load as figure 1	Y

APPENDIX H: Datasheet for tool installation

Use the following template and ask the Contractor to fill it:



leti

DPFT

ANNEXE H : Datasheet for tool installation

- 1) The datasheet informations allows CEA-LETI to design the fluid PID and the electrical PID.
- 2) These PIDs are then sent for verification and approval to the Contractor.
- 3) Hook Up and Fit Up will start after the official validation of PIDs by the Contractor.

Equipement Model :

List of Equipments & sub-equipments

Name	Location (Fab or sub-fab)	Type (Chiller, pump,...)	Model	Dimensions (L x w x h) in mm	Weight (Kg)	Supplied by
Chiller 1	Sub-Fab	Heat Exchanger	NESLAB HK-150	500 x 600 x 900	400	Contractor
Pump 1	Sub-Fab	Pump	iHx 600	300 x 900 x 800	200	CEA-LETI
Mainframe	Fab	Mainframe	xxx	2500 x 1300 x 2600	2500	Contractor

EXAMPLE

Facilities requirements			Description (b)	Connection		Consumption (e)				Pressure (bar) at the connection on the tool		Temp (° C)		Purity	Supplied by	Comments (ex: max length...) (f)
Fluid (a)	From	To		ID (c.)	Size (d)	Type	Min	Max	Average	Min	Max	Min	Max			
N2S	Facilities	Mainframe CH A	N2 Purge	G1	1/4"	VCRM	15	50	25	2.5	5	N/A	N/A	N/A	CEA-LETI	EXAMPLE
Glycol	Chiller 1	Mainframe CH A	Chilled Water	F1	3/8"	swg	10	20	12	2	3	15	18	N/A	Contractor	installed by CEA-LETI EXAMPLE
BCG	Facilities	Mainframe CH A	BCG proces	J2	1/4"	VCRM	1	2	1.2	1	1.3	N/A	N/A	N50	CEA-LETI	Purity : N50

The datasheet information allows CEA-LETI to design the fluid PID and the electrical PID (PID = Piping and Instrumentation Diagram).

These PIDs are then sent for verification and approval to the equipment Contractor.

Hook Up and Fit Up will start after the official validation of PIDs by the Contractor.

APPENDIX I: Risk Identification Sheet

Use the following template and ask the Contractor to fill it:

[Annexe I Fiche Identification Risques.xlsx](#)

cea leti		DPFT					
APPENDIX I : Risk Identification Sheet							
EQUIPEMENT REFERENCE & NAME :							
REFERENCE OF SAFETY DOCUMENTS PROVIDED							
EC Compliance certificate		<input type="checkbox"/>		Safety information and requirements in French		<input type="checkbox"/>	
RISK IDENTIFICATION							
Chemical risk : <input type="checkbox"/>							
Product name	Physical state (solid, liquid, gas)	DANGEROUSNESS				Usage concentration	Usage temperature
		Flammable	Combustive	Irritant / Harmful	Sensitizer / Toxic / CMR		
Explosion risk : <input type="checkbox"/>							
Under-pressure elements (bulb, pressure tank, ...):				Pressure :		Volume :	
Thermal risk : <input type="checkbox"/>							
Heating elements :				Temperature :			
Electrical risk : <input type="checkbox"/>							
Maximum voltage :				AC :		DC:	
Risk from ionising radiations : <input type="checkbox"/>							
Sealed radioactive material <input type="checkbox"/>		Presence of X-rays <input type="checkbox"/>		Open source radioactive material <input type="checkbox"/>			
Risk from non-ionising radiations : <input type="checkbox"/>							
UV <input type="checkbox"/>		Infrared <input type="checkbox"/>		High frequency <input type="checkbox"/>		Electromagnetic <input type="checkbox"/>	
Microwaves <input type="checkbox"/>		Permanent magnet <input type="checkbox"/>		Laser <input type="checkbox"/> Category (1-2-3-4) :			
Risk from handling during maintenance: <input type="checkbox"/>							
Manual handling <input type="checkbox"/>		Mechanical handling <input type="checkbox"/>		Handling device :			
Other risks :							
Equipment internal detections :							
Fire detection <input type="checkbox"/>				Leak detection <input type="checkbox"/>			
Gas detection <input type="checkbox"/>				Extraction control <input type="checkbox"/>			
Comments :							

APPENDIX J: SECS/GEM Compliance

Use the following template and ask the Contractor to fill it:

[Annexe J SECS/GEM Compliance Statement](#)